

FUZZ FACE - NPN				
	R1	33K	C1	2.2uf
	R3	8K2	C2	22uf
	R4	330R	C3	150pf (optional)
	R5	100K	C4	-----
	R6	GAIN POT 1KB	C5	10n
	R7	Jumper		
	R8	-----	Q1	BC108, BC109,
	R9	VOL POT 500KA	Q2	BC184, etc...
Colorsound One Knob				
	R1	10K	C1	100n
	R3	2K2	C2	10uf
	R4	82R	C3	220pf
	R5	150K	C4	-----
	R6	GAIN POT 1KB	C5	220n
	R7	Jumper		
	R8	-----	Q1	BC109
	R9	VOL POT 500KA	Q2	BC108
VOX Tonebender				
	R1	10K	C1	220n
	R3	8K2	C2	22uf
	R4	2K2	C3	220pf
	R5	47K	C4	-----
	R6	GAIN POT 1KB	C5	3n3 - 4n7
	R7	820R		
	R8	47K - 68K	Q1	NPN Ge 80-90hfe
	R9	VOL POT	Q2	NPN Ge 110-120hfe